

4-TERMINAL SINGLE AND MULTI-POSITION METER SOCKETS WITH OVERHEAD SERVICE ENTRANCE

Service Application				Reference
1Ø	2-Wire	120 Volts	0-30 Amperes	M-6
1Ø	2-Wire	240 Volts	0-100 Amperes	M-6
1Ø	2-Wire	277 Volts	0-60 Amperes	M-6
1Ø	2-Wire	480 Volts (Ungrounded)*	0-100 Amperes	M-6
1Ø	3-Wire	120/240 Volts	0-200 Amperes	M-7

Supplier	Socket Catalog Numbers				
	100 Amp.	200 Amp.	Horizontal, Ganged 100 Amp./Pos.	Vertical, Ganged 100 Amp./Pos.	Horizontal, Ganged 200 Amp./Pos.
Cutler Hammer	UHT-RS101B-CH	UHT-RS202B-CH UHT-RS213B-CH UT-H4203_-CH UTE4203_-CH	UHT-_R1121B-CH (2-5 Pos.) UHT-6R1131B-CH (6 Pos.)		UHT-_R2332T-CH (2-3 Pos.) UHT-4R2352T-CH (4 Pos.) UHT-_R2392TT-CH (5-6 Pos.)
Landis & Gyr/ Siemens (2)	UAT111-_P	HQ4G Series CQ4 Series UAT317-_P UAT417-_P	UA_311-_P (2-4 Pos.)		UA2717-_P (2 Pos.) UAT_71_-_P (3-6 Pos.)
Midwest	LRLPU412UA UHT-RS101B-MEP	LQRLPU414BA UHT-RS202B-MEP UHT-RS213B-MEP UT-H4203_-MEP	UHT-_R1121B-MEP (2-5 Pos.) UHT-6R1131B-MEP (6 Pos.)		UHT-_R2332T-MEP (2-3 Pos.) UHT-4R2352T-MEP (4 Pos.) UHT-_R2392TT-MEP (5-6 Pos.)
Milbank	U7487	U9550 U1773	U736_ (2-6 Pos.) U803_ (2-6 Pos.)	U2692 (2 Pos.) U2693 (3 Pos.)	U125_ (2-4 Pos.)(1) U287_ (2-6 Pos.)(1)
Murray	RJ192AX	RS192AX RH173CR	RN_91AR (2-4 Pos.)		
Square-D	UHT-RS101B-SQD	UHT-RS202B-SQD UHT-RS213B-SQD UT-H4203_-SQD	UHT-_R1121B-SQD (2-5 Pos.) UHT-6R1131B-SQD (6 Pos.)		UHT-_R2332T-SQD (2-3 Pos.) UHT-4R2352T-SQD (4 Pos.) UHT-_R2392TT-SQD (5-6 Pos.)

* Socket with 600 volt rating is required.

- (1) K1539 set screw connector kit required.
(2) Add "S" prefix for Siemens.

4-TERMINAL SINGLE POSITION METER SOCKETS WITH OVERHEAD SERVICE ENTRANCE 320 AMPERES (1, 2)

Service Application				Reference
1Ø	3-Wire	120/240 Volts	201-320 Amperes	M-7

Supplier	Socket Catalog Numbers
	320 Amp.
Cutler-Hammer	1008541-CH 1008541E-CH
Landis & Gyr/Siemens (4)	48104-82WI (3)
Midwest	1008541-MEP
Milbank	U4363-X-QG
Square-D	1008541-SQD

- (1) THESE UNITS HAVE A MAXIMUM CONTINUOUS RATING OF 320 AMPERES WHICH MUST NOT BE EXCEEDED.
(2) The load conductors may exit as two circuits.
Check with the manufacturer for the required connector kits.
(3) Requires K4802 anti-inversion kit installed in upper right meter jaw.
(4) Add "S" prefix for Siemens.

5-TERMINAL SINGLE AND MULTI-POSITION METER SOCKETS WITH OVERHEAD SERVICE ENTRANCE

Service Application				Reference
1Ø	3-Wire	208Y/120 Volts	0-100 Amperes	M-8
3Ø	3-Wire	240 Volts (grounded)	0-200 Amperes	M-8
3Ø	3-Wire	480 Volts	0-200 Amperes	M-9

Supplier	Socket Catalog Numbers				5th Terminal Catalog Number
	208Y/120 Volts, 1Ø		240 Volts, 3Ø	480 Volts, 3Ø	
	100 Amp.	200 Amp.*	200 Amp.	200 Amp.	
Cutler-Hammer		UT-H5213_-CH UTE5213_-CH	UT-H5213_-CH UTE5213_-CH	UT-H5213_-ND-CH	
Landis & Gyr/ Siemens (5)	UAT111-_P (1) UA2311-_P(2 Pos.)(1) UA3311-_P(3 Pos.)(1) UA4311-_P(4 Pos.)(1)	HQ5 Series CQ5 Series UAT317-_P (1) UAT417-_P (1) UAT_71-_P Series (2-6 Pos.) (1)	HQ5 Series CQ5 Series	HQ5NDU-9804- 8592 Series (2)	659-0121
Midwest		UT-H5213_-MEP	UT-H5213_-MEP	UT-H5213_-ND-MEP	
Milbank	U7487 (1)(3) U1773 (4)	U9550 U1773 (4)	U9550	U8624 (2)	5T24 or 5T8K2
Murray	RJ192AX (1)	RH173CR RS192AX (1)			RX012
Square-D		UT-H5213_-SQD	UT-H5213_-SQD	UT-H5213_-ND-SQD	

***Maximum service size is 100 amperes. These sockets may be used at the option of the customer.**

- (1) See 5th Terminal Catalog Number column.
- (2) This socket has a center phase disconnecting link.
- (3) 5th terminal must be bolted into place.
- (4) Requires 5th Terminal Catalog Number K5T.
- (5) Add "S" prefix for Siemens.

7-TERMINAL SINGLE POSITION METER SOCKETS WITH OVERHEAD SERVICE ENTRANCE

Service Application				Reference
3Ø	4-Wire	208Y/120 or 480Y/277 Volts	0-200 Amperes	M-10

Supplier	Socket Catalog Numbers			
	208Y/120 Volts, 3Ø		480Y/277 Volts, 3Ø	
	100 Amp.	200 Amp.	100 Amp.	200 Amp.
Cutler-Hammer		UT-H7213_-CH UTE7213_-CH		UT-H7213_-CH UTE7213_-CH
Landis & Gyr/ Siemens (1)		HQ-7 Series CQ-7 Series		HQ-7 Series CQ-7 Series
Midwest		UT-H7213_-MEP		UT-H7213_-MEP
Milbank	U7573	U7421 U9700	U7573	U7421 U9700
Murray		RH173GR		RH173GR
Square-D		UT-H7213_-SQD		UT-H7213_-SQD

- (1) Add "S" prefix for Siemens

4-TERMINAL SINGLE AND MULTI-POSITION METER SOCKETS WITH BREAKERS WITH OVERHEAD SERVICE ENTRANCE

Service Application				Reference
1Ø	2-Wire	120 Volts	0-30 Amperes	M-6
1Ø	2-Wire	240 Volts	0-100 Amperes	M-6
1Ø	2-Wire	277 Volts	0-60 Amperes	M-6
1Ø	2-Wire	480 Volts (Ungrounded)*	0-100 Amperes	M-6
1Ø	3-Wire	120/240 Volts	0-200 Amperes	M-7

Supplier	Socket Catalog Numbers	
	120/240 Volts, 1Ø	
	100 Amp./Pos.	200 Amp./Pos.
Cutler-Hammer	1MP-RRLB Series	1MP-RRLB Series MB816P200STD
General Electric	TMMR Series (1)	TMMR Series (1)
Midwest	R100 Series	R200 Series
Milbank	U7375 (1 Pos.) U5168-XTL-100-KK (1 Pos.) U2852 (2 Pos.) U2853 (3 Pos.) U2904 (4 Pos.) (2) U2905 (5 Pos.) (2) U2906 (6 Pos.) (2)	U7607 (1 Pos.) U5168-XTL-200-KK (1 Pos.) UAP5024-XL-KK (1 Pos.) U2862 (2 Pos.) (2) U2863 (3 Pos.) (2) U2864 (4 Pos.) (2)
Murray	MP__11RJB Series	MP__12RJB Series
Siemens	SP__11RJB Series SP__11RJBC Series	SP__12RJB Series SP__12RJBC Series
Square D	MPH22125 (2 Pos.) MPH33125 (3 Pos.) MPH44125 (4 Pos.) MPH55125 (5 Pos.) MPH66125 (6 Pos.)	MPH42200 (2 Pos.) MPH43200 (3 Pos.) MPH64200 (4 Pos.) MPH85200 (5 Pos.) MPH86200 (6 Pos.)

***Socket with 600 volt rating required.**

- (1) TMBPH by-pass and TMBR barriers required.
- (2) K1539 set screw connector kit required.

4 & 5-TERMINAL SINGLE POSITION METER SOCKETS FOR CUSTOMER-OWNED STREET LIGHTING

	<u>Service Application</u>		<u>Reference</u>
1Ø	3-Wire	240/480 Volts (grounded)	0-200 Amperes
			M-11

Supplier	Socket Catalog Numbers			5th Terminal* Catalog No.
	4-Terminal	5-Terminal		
	240/480 Volts, 1Ø (Rated 600 Volts)	240 Volts, 1Ø (Rated 300 Volts)	240 Volts or 480 Volts, 1Ø (Rated 600 Volts)	
Cutler-Hammer	UHT-RS213B-CH UT-H4213_-CH UTE4213_-CH			
Landis & Gyr/ Siemens (5)	HQ4G Series CQ4 Series UAT317-_P UAT417-_P	CQ5 Series HQ5 Series UAT317-_P (1) UAT417-_P (1)	CQ5 Series HQ5 Series	(1) 659-0121
Midwest	UHT-RS213B-MEP UT-H4213_-MEP			
Milbank	U1773 U9550	U1773 (2)	U1773 (2)	(2) K5T
Murray	RH173CR (4)	RS192AX (3)		(3) RX012
Square-D	UHT-RS213B-SQD UT-H4213_-SQD			

*The fifth terminal must be in the 9:00 position.

- (1) thru (3) see 5th Terminal Catalog Number column.
- (4) The 5th terminal shall be removed.
- (5) Add "S" prefix for Siemens.

TEMPORARY SERVICE ASSEMBLIES WITH OVERHEAD SERVICE ENTRANCE

	<u>Service Application</u>		<u>Reference</u>
1Ø	3-Wire	120/240 Volts	0-100 Amperes
			O-16

Supplier	Socket Catalog Numbers		
	120/240 Volts, 1Ø		
	60 Amp.	70 Amp.	200 Amp
Cutler-Hammer			MB816P200STD
Midwest	R038G (1,2) R038C010 (1,3)	R055G (1,2) R055C010 (1,3)	

- (1) MSB9 barrier strip required.
- (2) GFI circuit breaker
- (3) GFI outlet