

4-TERMINAL SINGLE AND MULTI-POSITION METER SOCKETS WITH DIRECT BURIED UNDERGROUND SERVICE LATERAL

	Service Application		Reference
1Ø	3-Wire	120/240 Volts	M-17
		0-200 Amperes	

Supplier	Socket Catalog Numbers		
	100 Amp./Pos.	200 Amp./Pos.	
	Multi-Position*	Single Position	Multi-Position*
Cutler-Hammer		UHT-RS213A-CH UT-H4213A-CH UTE4213A-CH	1009613-CH (2 Pos.) (6) 200A 1009614-CH (3 Pos.) (6) <u>270A</u> 1009615-CH (4 Pos.) (6) 350A 1009616-CH (5 Pos.) (6) 400A 1009617-CH (6 Pos.) (6) <u>400A</u>
Landis & Gyr/ Siemens (5)	UA2311-_P (2 Pos.) 200A UA3311-_P (3 Pos.) 200A UA4311-_P (4 Pos.) 200A	HQ-4GU-40404 CQ-4U-40604 UAT417-_P (1)	UA2717-_P (2 Pos.) 200A UA3717-_P (3 Pos.) (2) <u>270A</u> UA4719-_P (4 Pos.) (2) <u>270A</u> UA5719-_P (5 Pos.) (2) <u>270A</u> UA6719-_P (6 Pos.) (2) <u>270A</u>
Midwest		LTU276-BA LQRLPU414-12BA UHT-RS213A-MEP UT-H4213A-MEP	1009613-MEP (2 Pos.) (6) 200A 1009614-MEP (3 Pos.) (6) <u>270A</u> 1009615-MEP (4 Pos.) (6) 350A 1009616-MEP (5 Pos.) (6) 400A 1009617-MEP (6 Pos.) (6) <u>400A</u>
Milbank	L572 (2 Pos.) 200A L573 (3 Pos.) 200A L574 (4 Pos.) 200A L575 (5 Pos.) 225A L576 (6 Pos.) <u>270A</u>	U9551 U1773	U2872 (2 Pos.) (3)(4) 200A U2873 (3 Pos.) (3)(4) <u>270A</u> U2874 (4 Pos.) (3)(4) <u>360A</u> U2875 (5 Pos.) (3)(4) <u>400A</u> U2876 (6 Pos.) (3)(4) <u>400A</u>
Murray		RH173CR RS192A (1)	
Square-D		UHT-RS213A-SQD UT-H4213A-SQD	1009613-SQD (2 Pos.) (6) 200A 1009614-SQD (3 Pos.) (6) <u>270A</u> 1009615-SQD (4 Pos.) (6) 350A 1009616-SQD (5 Pos.) (6) <u>400A</u> 1009617-SQD (6 Pos.) (6) <u>400A</u>

***The main bus ampere rating is indicated for each multi-position listing. The underlined rating is restricted due to the largest service lateral that can be terminated in the unit.**

- (1) Use coverplate 38595-1 when required.
- (2) Use coverplate 56933 when required to cover hub opening, 2 required for 5 and 6 pos. sockets.
- (3) S2291-TO pedestal raceway required.
- (4) K1539 set screw connector kit required.
- (5) Add "S" prefix for Siemens.
- (6) Wiring trough required; 36" trough: Catalog No. 1008934-CH, 1008934-MEP or 1008934-SQD
54" trough: Catalog No. 1008845-CH, 1008845-MEP or 1008845-SQD
18" extension kit if required; Catalog No. 1009618-CH, 1009618-MEP or 1009618-SQD

5 & 7-TERMINAL SINGLE AND MULTI-POSITION METER SOCKETS WITH DIRECT BURIED UNDERGROUND SERVICE LATERAL

Service Application				Reference
3Ø	3-Wire	240(grounded) or 480 Volts	0-200 Amperes	M-18
3Ø	4-Wire	208Y/120 or 480Y/277 Volts	0-200 Amperes	M-19

Supplier	Single Position Socket Catalog Numbers			5th Terminal Catalog Number
	240 Volts, 3Ø	480 Volts, 3Ø	208Y/120 Volts, 3Ø 480Y/277 Volts, 3Ø	
	200 Amp.	200 Amp.	200 Amp.	
Cutler-Hammer	UT-H5213_-CH UTE5213_-CH	UT-H5213_-ND-CH	UT-H7213_-CH (6) UTE7213_-CH (6)	
Landis & Gyr/ Siemens (5)	HQ-5U-40405 CQ-5U-40605	HQ-5NDU-9804-8585 (1)	HQ-7U-40407 CQ-7U-40607	
Midwest	UT-H5213_-MEP	UT-H5213_-ND-MEP	UT-H7213_-MEP (6)	
Milbank	U9551	U8624(1)(2)	U7423 U9701	
Murray		RH173CR	RH173GR	
Square-D	UT-H5213_-SQD	UT-H5213_-ND-SQD	UT-H7213_-SQD (6)	
	Multi-Position Socket Catalog Numbers			
Milbank			U2732-XT-PED (2 Pos) (3, 4)	

- (1) This socket has a center phase disconnecting link.
- (2) A9064 heavy-duty closure plate required.
- (3) S2291-TO pedestal required.
- (4) K1539 set screw connector kit required.
- (5) Add "S" prefix for Siemens.
- (6) Cover plate required; Catalog no. ARP00002-CH, ARP00002-MEP or ARP00002-SQD

5 & 7-TERMINAL SINGLE POSITION METER SOCKETS WITH AC NETWORK UNDERGROUND SERVICE LATERAL (OUTDOOR INSTALLATIONS ONLY)

Service Application				Reference
1Ø	3-Wire	208Y/120 Volts	0-100 Amperes	M-18
3Ø	4-Wire	208Y/120 Volts	0-200 Amperes	M-19

Supplier	Socket Catalog Numbers			5th Terminal Catalog Number
	208Y/120 Volts, 1Ø		208Y/120 Volts, 3Ø	
	100 Amp.	200 Amp.*	200 Amp.	
Cutler-Hammer		UT-H5213_-CH UTE5213_-CH		
Landis & Gyr/ Siemens (5)	UAT111-_P (1)(4)	HQ-5U-40405 CQ-5U-40605 UAT417-_P (1)(4)	HQ-7U-40407 CQ-7U-40607	(1) 659-0121
Midwest		UT-H5213_-MEP		
Milbank	U1773 (2)	U9551	U9701	(2)K5T
Murray		RH173CR RS192A (3)	RH173GR	(3)RX012
Square-D		UT-H5213_-SQD		

***Maximum service size is 100 amperes. A 200 ampere socket is required for adequate space to terminate the service lateral cable.**

- (1) thru (3) see 5th Terminal Catalog Number column.
- (4) Use coverplate 38595-1 when required.
- (5) Add "S" prefix for Siemens.

**4 & 5-TERMINAL SINGLE AND MULTI-POSITION METER SOCKETS
WITH CONCRETE ENCASED UNDERGROUND SERVICE LATERAL
(NOT FOR AC NETWORK)**

Service Application				Reference
1Ø	3-Wire	120/240 Volts	0-200 Amperes	M-17
3Ø	3-Wire	240 Volts (grounded)	0-200 Amperes	M-18

Supplier	Socket Catalog Numbers*		
	120/240 Volts, 1Ø		240 Volts, 3Ø
	100 Amp.	200 Amp./Pos.	200 Amp.
Cutler-Hammer	UHT-RS111B-CH (5)	UHT-RS213B-CH (5) UT-H4213B-CH (5) UTE4213B-CH (5)	
Landis & Gyr/ Siemens (4)	UA2311-_P (2 Pos.) (1) UA3311-_P (3 Pos.) (1) UA4311-_P (4 Pos.) (1) UAT111-_P (1)	HQ-4GU-40404 CQ-4U-40604 UA2716-_P (2 Pos.) (2) UAT417-_P (1) UA2717-_P (2 Pos.) (2) UA3717-_P (3 Pos.) (2) UA4719-_P (4 Pos.) (2) UA5719-_P (5 Pos.) (2) UA6719-_P (6 Pos.) (2)	HQ-5U-40405 CQ-5U-40605
Midwest	UHT-RS111B-MEP (5)	UHT-RS213B-MEP (5) UT-H4213B-MEP (5)	
Milbank	U7588	U9551 U2872 (2 Pos.) (3) 200A U2873 (3 Pos.) (3) <u>270A</u>	U9551
Murray		RH173CR	
Square-D	UHT-RS111B-SQD (5)	UHT-RS213B-SQD (5) UT-H4213B-SQD (5)	

***The main bus ampere rating is indicated for each multi-position listing. The underlined rating is restricted due to the largest service lateral that can be terminated in the unit.**

- (1) Coverplate 38595-1 to cover hub opening required.
- (2) Use coverplate 56933 when required to cover hub opening, 2 required for 5 & 6 pos. sockets.
- (3) K1539 set screw connector kit required.
- (4) Add "S" prefix for Siemens.
- (5) Cover plate required; Catalog no. ARP00002-CH, ARP00002-MEP or ARP00002-SQD

**JOINT USE TERMINATION PEDESTAL
FOR COMMUNICATIONS EQUIPMENT WITH DIRECT BURIED SERVICE**

Supplier	Catalog Numbers
Milbank	U4329-O(1)

(1) This unit is intended to work with all manufacturers' metering pedestals.